

## **TMS370 v1.6 ERRATA SHEET**

- Serial Ports comm1-comm8 available
- CP2101 USB drivers compatible (Comm -> USB converters, Virtual Com Port Drivers)

**Requirements:**

**Win2000/XP/Win2003 OS only \***

**Follow next steps to fix errors:**

1. "START" -> "Control panel" -> "Add/Remove programs"
2. Remove previous version of tms370 control software
3. Install new version 1.6 tms370.exe
4. Un-mount (open/ remove) update jumper to enter update mode \*\*
5. Power ON tms370 programmer board
6. "START" -> "update370.exe"
7. Select comm1 or comm2 serial port and start the update program
8. Power OFF tms370 programmer board
9. Mount (short/ insert) update jumper to leave update mode \*\*
10. Start the tms370.exe control software\*\*\*

**\*NOTE: Version 1.6 not compatible with Win95/98 OS**

**\*\*NOTE See TMS370 User's Manual for details**

**TMS370 v1.6 hardware update SW requirements:**

- Free Comm1, Comm2 Serial ports
- tms370uf.hex file in current directory /size 16.970/
- tms370\_update.exe

**\*\*\*NOTE Click menu item "Help" -> "About" -> "Version"**

**Make sure, that TMS370 control software 1.6 displayed**